

PRODUCT DOCUMENT

Quick Start Guide

Illustra Essentials Gen4 2MP Fixed Bullet • Installation and first-setup reference

1. Before installation

Confirm the camera, mounting hardware and printed quick guide are present. Inspect the housing and accessories for visible shipping damage before installation.

2. Mount the camera

Use the mounting template to mark the mounting points. Drill the required holes, install suitable anchors and secure the camera using the supplied screws. Route the cable through the appropriate cable entry before closing the housing.

3. Connect power and network

Method	Connection
PoE	Connect the RJ-45 network cable to a PoE-compatible network device supplying IEEE 802.3af Class 3 power.
12V DC	Connect the 12V DC power cable to the camera's DC 12V terminal.

4. Find the camera on the network

The published guide lists a default IP address of **192.168.1.168** with DHCP enabled. If a DHCP server is available, the camera can obtain an address automatically. Use the camera discovery / network method appropriate to your installation.

5. Open the web interface

Open the camera's assigned IP address in a supported web browser and sign in with an authorized administrator account. Change default credentials immediately if they are still in use.

6. Basic configuration checklist

Item	Recommended first action
Date / time	Set the correct time zone and synchronize time using your approved NTP configuration.
Network	Confirm DHCP/static addressing, gateway and DNS settings.
Video stream	Confirm 1920 × 1080 where required and select H.264/H.265 according to recorder and bandwidth requirements.
Day / night	Verify True Day/Night and IR operation at the installation location.
WDR	Enable/configure WDR for scenes with strong backlight or high contrast.
Corridor mode	Use for narrow vertical spaces such as hallways and aisles when required.

Item	Recommended first action
Security	Use strong administrator credentials and HTTPS where supported by the deployment.

7. Final installation check

Verify live video, focus, viewing angle, IR operation, recording/streaming, network connectivity and cable sealing before handing the system over.

Important: This is a professionally formatted quick-start reference prepared from the published manufacturer installation/configuration guide; it is not the manufacturer's original quick-guide artwork.